





Standard Military vehicle wiring information
(letters are marked next to connector contacts)

PIN PINOUT



SOCKET PINOUT



A, C, H Blackout tail lights and blackout clearance lights (all three pins are electrically connected together within vehicle's wiring harness)

B Brake light and left turn signal light

D Ground

E Tail lights / Clearance lights

F Blackout brake light

J Brake light and right turn signal light

K Auxiliary power feed used on semi tractor only

L, M, N Not used